BEFORE PERMANENTLY INSTALLING THE INTELLICONNECT SYSTEM, IT IS BEST TO MAKE SURE THAT THE SYSTEM WILL BE ABLE TO MAINTAIN A RELIABLE WIRELESS CONNECTION FROM THE EQUIPMENT PAD TO THE HOME ROUTER.

READ AND FOLLOW THE INSTRUCTIONS BELOW TO HELP ENSURE A RELIABLE WIRELESS CONNECTION BETWEEN THE INTELLICONNECT SYSTEM AND A HOME ROUTER.

Testing Wireless Signal Strength Using IntelliConnect

1. Ensure the power is turned off at the circuit breaker before wiring the IntelliConnect system.
2. Open the enclosure by unfastening the two retaining clips at the top of the enclosure
3. Remove the retaining screw securing the high voltage wiring compartment cover and remove the high voltage cover.
4. At the proposed mounting location, bring 120/240V power into the high voltage wiring compartment and temporarily wire to screw terminals marked L1 and L2 (see **Figure 1**).

   Note: Cap the ground wire to ensure electricity does not arc to a hot wire or the control board.
5. Reinstall the high voltage cover over the high voltage wiring compartment and secure with the retaining screw.
6. Return power to the enclosure at the circuit breaker. The IntelliConnect will now enter access point mode for ten (10) minutes and the LINK LED will blink green.
7. Open your computer, smartphone or tablet's wireless settings.

   To open Wireless Settings on smartphones or tablets: Go to Settings>Wireless or

Testing Wireless Signal Strength with a Smart Device

There are many apps and tools available on smartphones or other mobile devices that allow a user to check the strength of wireless signals.

Wireless router signal strength can vary over time and just because a signal is strong today does not guarantee a strong signal tomorrow. Signal strength can be affected by other users in close proximity accessing their routers.

When using a Wireless Signal Monitoring app the lower the dBm reading the better. For example, a signal strength of -40dBm is good and a strength of -80dBm is considered bad. A signal strength between -30dBm and -60dBm is